



## PULSE 50 230V 6V/12V/24V



### Обзор

#### PULSE 50 230V 6V/12V/24V

cod. 807588

6/12/24V electronic, automatic battery charger for WET, GEL, AGM, MF, SPIRAL, START-STOP batteries, for automatic charging/maintenance (PULSE TRONIC), for recovering sulphated or very low batteries and vehicles start aid.

It is very easy to use, thanks to the automatic recognition of the type of battery, and the presence of a user-friendly keypad. The innovative Power Stream technology guarantees better performance, up to 50% more than traditional battery chargers thanks to more effective and complete control of the charging process, to notably faster charging times and maintenance of the optimal battery conditions, which guarantee a longer working life.

The Pulse Tronic technology guarantees optimal battery charging over 8 phases which test, monitor, increase and maintain the charge state.

#### Features:

- automatic charging/maintenance, BOOST quick charge and START aid
- SMPS (Switch Mode Power Supply) Technology
- Pulse Tronic charge with pulsed charge holding
- LED signalling of the charge state, end of charge and protection intervention
- sulphated battery recovery selection
- clamps not powered if disconnected from the battery - anti-spark device, protection against short-circuits, polarity reversal, overvoltage at input and faulty battery.

Fit with PFC device.

### Технические данные

<b>CODE</b>	КОД 807588	<b>A<sub>EN</sub></b>	ТОК КОНВЕНЦИОНАЛЬНОГО ЗАРЯДА EN60335-2-29 40 / 40 / 20 A		РАЗМЕРЫ 33 - 10 - 16 cm
<b>V<sub>1PH</sub></b>	ОДНОФАЗНОЕ НАПРЯЖЕНИЕ СЕТИ 230 V	<b>A<sub>1V/C</sub></b>	ТОК ЗАПУСКА 1V / C EN60335-2-29 40 (Boost)/70 (Start) A		БЕС 3,5 kg



## PULSE 50 230V 6V/12V/24V



ЧАСТОТЫ СЕТИ 50 / 60 Hz



МИН. НОМИНАЛЬНАЯ ССЫЛКА  
ПОТЕНЦИАЛ 10 Ah



КОД EAN 800489795906 1



ПОГЛОЩЕННАЯ МОЩНОСТЬ ЗАРЯДА  
600 W



МАКС. НОМИНАЛЬНАЯ ССЫЛКА  
ПОТЕНЦИАЛ 600 Ah



ЧАСТЕЙ / ПАЛЛЕТ 99 pz/pallet



НАПРЯЖЕНИЕ ЗАРЯДКИ 6 / 12 / 24 V



РЕГУЛИРОВКА ПОЗИЦИИ 1



ЧАСТЕЙ / ПАЛЛЕТ - В 88 pz/pallet - В



ТОК ЭФФЕКТИВНОГО ЗАРЯДА 45 /  
45 / 23 A

---

### Входящие в комплект аксессуары